

PM-1060/PM-1120 Desktop Mixer Amplifier with MP3/FM Tuner/Bluetooth

Product ID: PM-1060/PM-1120



Short Description

Rated output power: 60W/120W

Built-in MP3 player, FM tuner and bluetooth

2 MIC input, 1 AUX input, 1 AUX output

Description

? Build-in MP3 player, FM tuner and bluetooth

? 2 MIC input, MIC1 with muting function, 1 AUX input; 1 AUX out for link

? Individual/Master volume control for all inputs, BASS and TREBLE tone control

? Output: 70V, 100V, 4~16?

? With bluetooth player

? LED indicator

? Short circuit, overload, high temperature protection

Specification

Model	PM-1060	PM-1120
-------	---------	---------

Rated output power		60W	120W
Output	Low impedance	4-16?	
	70V	51?	41?
	100V	167?	83?
AUX output level		0.775V (0dBV)	
Input level	MIC 1,2	600?, 5-10mV (unbalanced)	
	AUX	10K?, 150-470mV (unbalanced)	
Frequency response		60Hz-15KHz (± 3 dB)	
T.H.D.		<0.5% at 1KHz, 1/3 rated output power	
S/N ratio	MIC 1,2	?72dB	
	AUX	?85dB	
Tone	Bass	± 10 dB at 100Hz	
	Treble	± 10 dB at 12KHz	
Muting function		MIC1 overrides other input signals at 0~30dB	
Controls		Volume, tone/treble, mute, power	
Protection		AC fuse, overload, short circuit, high temperature	
		FUSE $\times$ 4A	FUSE $\times$ 8A
Cooling fan		DC 12V FAN	
LED indicator		AC: POWER, level: 2?4?6?8?10	
Power supply		AC220~240V, 50-60Hz	
Power consumption		84W	168W
Power cord		(3 $\times$ 0.5 mm ²) $\times$ 1.5M (standard)	
Product dimension (mm)		72(H) $\times$ 305(W) $\times$ 275(D)	
Packing dimension (mm)		130(H) $\times$ 345(W) $\times$ 345(D)	
Net weight (Kg)		5.00	5.50
Packing weight (Kg)		5.70	6.20

Product Gallery

