

EF-81/EF-82, 8x1/8x2 Channel Pre Amplifier with Remote Paging

Product ID: EF-81/EF-82



Short Description

1/2 CH line output for amplifiers
2 CH MIC/Line input, 6 CH line input
With remote paging MIC input

Description

- ? 1 or 2 Channel line output for amplifiers
- ? 2 Channel MIC/Line input, 6 Channel line input, each input with individual volume adjustment and power switch
- ? 8 Channel gain control, while 2 Channel with 3 band EQ, talkover and phantom power switch
- ? Output with 2 tone control and mute switch
- ? With remote paging MIC input (RJ45 interface)
- ? LED indicators: Power
 - SIG and CLIP for each input channel
 - SIG, -10dB, CLIP for output channel

Specification

Model		EF-81	EF-82
Output Level / Impedance		0dB / 600 Ω Balanced	
Input sensitivity /Impedance	Mic Input (CH1-2)	-50dB~ -16dB / 20K Ω Balanced	
	Line Input (CH1-6)	-30dB~ +4dB / 20K Ω Balanced	
	Remote Input	0dB / 600 Ω balanced	
Frequency Response (± 1 dB)		20Hz - 20kHz	
T.H.D		<0.01%	
Closstalk		>70dB	
Output Channel Quantity		1 CH	2 CH
Equalization	Input	High: 12 kHz $\pm$ 15 dB Mid: 2.5 kHz $\pm$ 15 dB Low: 80 Hz $\pm$ 15 dB	
	Output	High: 10 kHz $\pm$ 15 dB Low: 100 Hz $\pm$ 15 dB	
S/N Ratio		>90dB	
Power Source		AC 100-240 V, 50/60Hz / DC24V	
Net Weight (Kg)		9.0	
Dimensions (mm)		482W x 44H x 320D	

Product Gallery



