

H-6700D Digital IR Receiver

Product ID: H-6700D



Short Description

Accommodates up to 32 different languages
With channel selector and headphone connector
LCD display battery and reception status

Description

- ? Packet size wireless handheld unit
- ? Accommodates up to 32 different languages
- ? Channel selector and headphone connector
- ? Power on/off switch and volume level control
- ? Powered by (2xAA) rechargeable batteries
- ? Aluminum carrying cases provided for receivers
- ? 2-digit LCD display with battery and reception status indication
- ? Compatible with **Bosch** system

Specification

Item	Parameter
Receiving sensitivity	-101dBm
Angle of half sensitivity	$\pm 50^\circ$
Headphone output level at 2.4V	450 mVrms (Speech at maximum volume, 32 ohm headphone)

Headphone output frequency range	20Hz to 10KHz
Headphone output impedance	32?
Max. signal-to-noise ratio	78dB(A)
Supply voltage	1.8 to 3.6 V, nominal 2.4 V
Power consumption at 2.4V (battery voltage)	60mA (speech at maximum volume, 32 ohm headphone)
Power consumption (standby)	60mA
Dimension (mm)	157×49×25
Operating temperature range	0-40°
N.W (Kg)	150g without battery