LY International Electronics Co., Ltd - Room 1206 Aoyuan Jinsha Plaza Business Building, No. 26 Jinlong Road Nansha District, Guangzhou China, 511458
Phone: +86-20-39390663 - Email: sales@lyintl.com

ED-120/ED-240/ED-360/ED-480L/ED-600L 5 Zone Digital Mixer Amplifier with Remote Paging



Product ID:
ED-120/ED-240/ED-360/ED-480L/ED-600L

Short Description
Rated output power: 120W/240W/360W/480W/600W
6 MIC input, 3 AUX input
With remote paging MIC input

Description
? Rated output power: 120W/240W/360W/480W/600W
? 6 MIC input (3 XLR), 3 AUX input, MIC1 with priority muting function, input individual volume control, treble & bass & master volume control
? 5 zone 100V speaker output, 1 zone 4? speaker out (ED-120/ED-240/ED-360)
? 2 line amplifier input, 2 line amplifier out
? With remote paging MIC input (RJ45 interface)
? Telephone paging function (Euro block)
? Music on hold fuction (Euro block)
? Siren & Chime function
? LED indicators: Power, SIG, -20dB, -10dB, 0dB, CLIP & protect, zone selector


Specification

Model	ED-120	ED-240	ED-360	ED-480L	ED-600L

Rated output power	120W	240W	360W	480W	600W
Output / Impedance	100V(83?), 70V(42?), 25V(5.2?), 22V(4?)	100V(42?), 70V(21?), 25V(2.6?), 31V(4?)	100V(28?), 70V(13.6?), 25V(1.7?), 38V(4?)	100V (20.8?)	100V (16.7V)
Input sensitivity	Channel 1-3, MIC: -54dB to -6dB Variable / 20K? balanced Channel 4-6, Line: -34dB to +14dB Variable / 20K? balanced Remote paging, MIC: 0dB / 20K? balanced Tel-paging: -17dB / 600? balanced Amp/line in: 0dB/10K? unbalanced				
Frequencey response	80Hz-18KHz				
T.H.D.	<0.1%				
S/N ratio	>80dB				
Grapic source (±12dB)	125Hz, 250Hz, 500Hz, 1KHz, 2KHz, 4KHz, 8KHz				
Power supply	AC230V, 50/60Hz				
Protection	Overheat, overload				
Net weight (Kg)	6.3	7.3	8.3	5.5	5.5
Product dimension (WxDxH)	420x320x88mm				

Product Gallery




CD/MP3/Tuner player
MP3/Digital tuner
Network radio with USB/Bluetooth
Telephone pager/PBX
Power amplifier