LY International Electronics Co., Ltd - Room 1206 Aoyuan Jinsha Plaza Business Building, No. 26 Jinlong Road Nansha District, Guangzhou China, 511458
Phone: +86-20-39390663 - Email: sales@lyintl.com

PB-8070Z/PB-8130Z/PB-8260Z/PB-8360Z/PB-8500Z 6 Zone Mixer Amplifier

Product ID: PB-8070Z/PB-8130Z/PB-8260Z/ PB-8360Z/PB-8500Z



Short Description

Rated output power: 60W/120W/240W/350W/500W
2 AUX input, 3 MIC input, 1 AUX output for link

Description

? 6 zone 100V speaker output with individual switch and LED indicator
? 2 AUX input, 3 MIC input, MIC1 with muting function; 1 AUX out for link
? Individual/Master volume control for all inputs, BASS and TREBLE tone control
? Output: 70V, 100V, 4~16?
? Short circuit, overload and high temperature protection

Specification

Model	PB-8070Z	PB-8130Z	PB-8260Z	PB-8360Z	PB-8500Z
Rated output power	60W	120W	240W	350W	500W
Output Low impedance			4-16?		

	70V	70?	38?	19?	14?	10?
	100V	143?	77?	39?	28?	20?
AUX output level		0.775V (0dBV)				
6 Zones output		100V				
Input level	MIC 1,2,3	600?, 10-15mV (unbalanced)				
	AUX 1,2	10K?, 200-470mV (unbalanced)				
Frequencey response		60Hz-15KHz (±3dB)				
T.H.D.		<0.5% at 1KHz, 1/3 rated output power				
S/N ratio	MIC 1,2,3	?72dB				
	AUX 1,2	?85dB				
Tone	Bass	±10dB at 100Hz				
	Treble	±10dB at 12KHz				
Muting function		MIC1 overrides other input signals at 0~30dB				
Controls		Volume, tone/treble, mute, power				
Protection		AC fuse, Overload, Short circuit, high temperature				
		FUSE×4A	FUSE×4A	FUSE×6A	FUSE×6A	FUSE×8A
Cooling fan		DC 12V FAN				
LED indicator		AC: POWER, level: 2?4?6?8?10				
Power supply		AC220~240V, 50-60Hz				
Power consumption		95W	185W	350W	485W	675W
Power cord		(3×0.75 mm2)×1.5M (standard)				
Product dimension (mm)		89(H)×483(W)×366(D)				
Packing dimension (mm)		185(H)×520(W)×435(D)				
Net weight (Kg)		10.5	11.5	13.8	14.5	15.5
Packing weight (Kg)		11.80	13.10	15.40	15.80	17.20

Product Gallery

