

# PM-210U/PM-310U/PM-610U/PM-1010U 6 Zone Mixer Amplifier with MP3/Tuner

## Product ID:

PM-210U/PM-310U/PM-610U/PM-1010U



## Short Description

Rated output power: 60W/120W/250W/350W

Combined with MP3/Tuner/USB/SD card inputs

## Description

- ? 6 channel integrated mixer/zone amplifier
- ? Combined with MP3/Tuner/USB/SD card inputs
- ? Individual channel volume selection and output level indication
- ? 4 MIC inputs with volume selector and 3 AUX line inputs
- ? 1 line output for additional mixer/amplifier
- ? 4-6? single speaker output, 6 channel 100V output
- ? 2 levels priority muting function: MIC 1>chime
- ? Treble and bass volume control separately
- ? LED digital tube displaying volume, playing status, programme number and etc.
- ? 5 LED meter for monitoring volume output in each zone
- ? Output short circuit protection and caution

## Specification

Model	PM-210U	PM-310U	PM-610U	PM-1010U
-------	---------	---------	---------	----------

Output Power	60W	120W	250W	350W
Output Regulation	±3dB from off-load to full load			
Speaker Output	4-16Ω single output and 6 channel 100V output			
Input	MIC: ±3mV (unbalanced)			
	Line: ±300mV (unbalanced)			
Frequency Response	80Hz-16KHz (±3dB)			
Distortion	±1% at 1KHz			
S/N	MIC: ±74dB			
Tone	Bass: ±10dB at 100Hz			
	Treble: ±10dB at 10KHz			
Protection	DC voltage; overload; short-circuit			
Muting Function	MIC 1 overrides other signal inputs			
Power Requirements	AC220-240V/50-60Hz			
Power Consumption	120W	250W	500W	650W
Gross Weight (Kg)	11.7	13.5	16	17
Net Weight (Kg)	10	11.5	14	15
Dimensions (mm)	418x88x338			

## Product Gallery

