

PM-2106/PM-2112 6 Zone Mixer Amplifier with MP3/Tuner

Product ID: PM-2106/PM-2112



Short Description

Rated output power: 60W/120W

Combined with pre-amplifier/MP3/tuner/power amplifier

3 AUX input, 2 MIC input, 1 AUX output for link

Description

? Combined with pre-amplifier, MP3 player, tuner and power amplifier.

? 6 zones output.

? USB, SD card and other memory equipments to provide MP3 sound source.

? 2 MIC input, 3 AUX input, and 1 AUX output for link.

? Muting function.

? Individual volume control. Bass and treble tone control.

? A five-element LED level meter is provided for the quick and easy visual monitoring of sound level.

Specification

Model	PM-2106	PM-2112
Output Power	60W	120W
Output Regulation	<3dB	

Output	Speaker: 100V	
	AUX: 1V	
Input	MIC 1, 2: 3mV(± 0.5 mV), unbalanced	
	AUX 1, 2, 3: 300mV(± 30 mV), unbalanced	
	MP3: 230mV~280mV	
	FM: 87.5MHz-108.0MHz	
Frequency Response	65Hz~20KHz (± 3 dB)	
Distortion	Less than 1% at 1KHz, 1/3 rated power	
Line S/N	>80dB	
Mic S/N	>80dB	
Tone Adjustment	Bass: ± 12 dB at 100Hz	
	Treble: ± 10 dB at 10KHz	
Protection	AC fuse, DC voltage, overload, short circuit	
Muting Function	MIC 1 overrides other input signals with 0~-30dB attenuation	
Power Requirements	AC 220~240 V / 50~60 Hz	
Power Consumption	100W	200W
Net Weight (Kg)	7.2	8.9
Gross Weight (Kg)	8.5	10.3
Dimensions (mm)	485×340×88	

Product Gallery

