

ED-35M/ED-65M Desktop Digital Amplifier with MP3 Record Player/FM Tuner/Bluetooth

Product ID: ED-35M/ED-65M



Short Description

Rated output power: 35W/65W
Combined with MP3/FM/bluetooth
3 MIC input, 2 AUX input

Description

- ? Combined with MP3 record player, digital FM tuner and bluetooth 2.1
- ? Small-sized designed desktop amplifier
- ? 3 MIC input, 2 AUX input. MIC1 (XLR jack) with priority muting function
- ? 70V/100V/4?/8? output
- ? Telephone paging function (Euro block)
- ? 3 channel input individual volume control, treble & bass & master volume control
- ? With power, signal, -20dB, limiter and protect LED indicators

Specification

Model	ED-35M	ED-65M
-------	--------	--------

Rated output power	35W	65W
Output / Impedance	100V / 285? 70V / 140? 16.8V / 8? 11.8V / 4?	100V / 154? 70V / 75? 22.8V / 8? 16.1V / 4?
Input sensitivity	MIC: -54dB to -10dB Variable / 20K Ω balanced Line: -34dB to +10dB Variable / 10K Ω unbalanced Tel-paging:-15dB / 600 Ω balanced Music on hole: 0dB / 600 Ω balanced	
Frequency response	80Hz-18KHz	
T.H.D.	<0.5%	
S/N ratio	>81dB	
Tone control effect	100Hz, 10KHz $\pm$ 10dB	
Power supply	AC110~240V, 50/60Hz	
Protection	Overheat, overload	
Net weight	3.2Kg	3.6Kg
Product dimension (WxDxH)	270x230x76mm	
Media player		
Frequency range (FM)	87.5~108MHz	
Channel step (FM)	50KHz	
Sensitivity (FM)	2 uV at 30dB S/N	
S/N ratio	FM: >60dB MP3: >80dB	
Audio codec	MPEG 1/2/5 layer 2/3 decoding (8KHz-48KHz) WMA V4, V7, V8, V9(L1, L2) decoding (8KHz-48KHz)	
MP3/WMA compatible media	MP3 USB memory sticks up to 16GB (FAT32)	

Product Gallery

