

# PM-2813RF Digital AM/FM Tuner

**Product ID:** PM-2813RF



## Short Description

FM/AM tuner  
LCD display  
1U design

## Description

### Description:

? FM frequency range: 87.5 - 108 MHz, AM frequency range: 522 - 1620KHz  
? LCD display  
? 1U design

## Specification

|                  |              |
|------------------|--------------|
| Model            | PB-2813RF    |
| Audio output     | 500mVrms     |
| Output impedance | 1K Ohm       |
| Input voltage    | AC 220V 60Hz |

|                    |                         |
|--------------------|-------------------------|
| Power consumption  | 6W                      |
| Memory             | 60 station              |
| AM                 |                         |
| Frequency range    | 522-1620 KHz STEPS 9KHz |
| Sensitivity        | 16dB                    |
| S/N                | 40dB                    |
| Distortion         | 0.30%                   |
| Frequency Response | 80Hz-4KHz               |
| FM                 |                         |
| Frequency range    | 87.5-108MHz STEPS 50KHz |
| Sensitivity        | 20dB                    |
| S/N ratio          | 40dB                    |
| Distortion         | 0.20%                   |
| Frequency Response | 20Hz-20KHz              |
| Antenna Impedance  | 75 Ohm                  |

**Product Gallery**

