

# PP-730 Multi-functional Portable Wireless PA Amplifier (MP3/Tuner/USB/SD/Recording/Bluetooth)

**Product ID:** PP-730



## Short Description

RMS power: 40W MAX

With FM/USB/SD/MP3/Recording/Bluetooth

2 wired MIC & 1 AUX & 1 guitar input, 1 AUX output

12" full range speaker and 1" 8? horn tweeter

## Description

### Description

All in one design, VHF wireless PA Speaker system, build-in DC 12V 7AH rechargeable battery, easy carrying and portable use.

? RMS power: 40W MAX

? With FM/USB/SD MP3 player/Recording/Bluetooth

? 12" full range speaker and 8? 35W horn tweeter

? 2 wired MIC input, 1 AUX input, 1 guitar input, 1 AUX output

? With dual channel wireless MIC input ( handheld, lapel MIC or headset MIC option)

## Specification

Model No.	PP-730
RMS output power	40W MAX
Input	2 wired MIC, 2 wireless MIC input, 1 AUX input, 1 guitar input
Output	1 AUX output
Line output level	500mV
MIC input sensitivity	5mV
Line input sensitivity	200mV
Build-in features	Optional VHF wireless MIC (handheld, lapel MIC or headset MIC)
	MP3 player through USB & SD slot input
	With tripod jack at the bottom of the machine
	Digital FM tuner
	Wired & wireless MIC input
	Treble & bass control
	Digital echo control
	MIC with priority function
	Individual volume control of CD/MP3/AUX/FM&AM/wired/wireless MIC
	With LCD display
T.H.D.	<1.0% (at 10W)
Treble & bass adjustment gain	±10dB
S/N ratio	>90dB
Frequency response	40Hz - 20KHz
Frequency channel	Dual channel
Wireless service range	MAX 35m in VHF
Wireless channel	0-98 infrared auto match
Wireless frequency range	VHF 165~265MHz
Oscillating mode	±0.005% quartz control phase locked
Speaker	12" full range speaker and 1" 8? 35W horn tweeter
Operating temperature	-25°C ~ 45°C
Power supply	AC100~250V / 50~60Hz, 1.0A

	External DC 12V 5AH
	Build-in DC 12V 7AH rechargeable battery
Rated consumption power	100W
Material	ABS engineering plastic body
Net weight (Kg)	13.1
Gross weight (Kg)	14.5
Product dimension (mm)	310 x 340 x 570
Packing dimention (mm)	423 x 398 x 660

## Product Gallery

