

ED-35/ED-65 Desktop Digital Amplifier

Product ID: ED-35/ED-65



Short Description

Rated output power: 35W/65W
3 MIC input, 2 AUX input

Description

- ? Small-sized designed desktop amplifier
- ? 3 MIC input, 2 AUX input. MIC1 (XLR jack) with priority muting function
- ? 70V/100V/4?/8? output
- ? Telephone paging function (Euro block)
- ? 3 channel input individual volume control, treble & bass & master volume control
- ? With power, signal, -20dB, limiter and protect LED indicators

Specification

Model	ED-35	ED-65
Rated output power	35W	65W
Output / Impedance	100V / 285?	100V / 154?
	70V / 140?	70V / 75?
	16.8V / 8?	22.8V / 8?

	11.8V / 4?	16.1V / 4?
Input sensitivity	MIC: -54dB to -10dB Variable / 20K? balanced Line: -34dB to +10dB Variable / 10K? unbalanced Tel-paging:-15dB / 600?balanced	
Frequency response	80Hz-18KHz	
T.H.D.	<0.5%	
S/N ratio	>80dB	
Tone control effect	100Hz, 10KHz±10dB	
Power supply	AC100~240V, 50/60Hz	
Protection	Overheat, overload	
Net weight	3.2Kg	3.6Kg
Product dimension (WxDxH)	270x230x76mm	

Product Gallery

