

HS-8300 4 Zone Intelligent Extending Power Amplifier for HS-8328

Product ID: HS-8300



Short Description

4 zones output

Each zone 2x30W 8? stereo output

1xHS-8328 can connect 16xHS-8300

Description

HS-8300 is zone extended power amplifier used for multi-room network music system.

Each set of HS-8300 is able to provided 4 additional zones for the user, in order to meet the additional zones requirement. One piece HS-8328 main host is able to connect 16 pieces of HS-8300 extending amplifier by "hand-in-hand" or star connection mode. Each HS-8300 has its own address ID, which the user can change it according to his own requirement.

- ? RJ45 control signal transmission cable
- ? Support hand-in-hand connection between HS-8300
- ? Supply power output for 4 zones, each zone 2x30W 8? stereo output
- ? Input power supply switchable between 115V and 230V
- ? One HS-8328 can connect upto 16 sets of HS-8300
- ? One HS-8300 can connect with 4 sets of HS-828R room controller

Specification

Item		Indicator
Number of partition		4 partitions
Audio frequency indicator	Rated output power	Stereo, 8×30W/8?
	Frequency response	20Hz-20kHz (±0.5dB)
	Total harmonic distortion	<0.3% (f=1kHz, 1/3 of rated output power)
	Signal to noise ratio	>81dB
Room controller interface		Using RJ45 network cable
Power amplifier output protection		Any partition has output short-circuit, overloading and direct current protection
Power supply		AC115V or 230V/50-60Hz
Consumed power		<350W
Power protection		AC220V/F6A
Dimension of outer packing (mm)		(L×W×H) 340×340×160
Dimension (mm)		(L×W×H) 230×285×65
Gross weight (Kg)		3.2
Net weight (Kg)		2.8

Product Gallery



HS-8328 System Connection Diagram

