

PB-3060/PB-3120/PB-3240/PB-3360/PB-3480 60W-480W Single Zone Mixer Amplifier

Product ID:

PB-3060/PB-3120/PB-3240/PB-3360/PB-3480



Short Description

Rated power: 60W/120W/240W/360W/480W

3 MIC input, 2 AUX input

Description

Classical mixer amplifier comes with 3 microphone input and 2 aux input, mic 1 is provided with priority and muting function.

Input individual volume control and master volume control are provided.

? 2 AUX input, 3 MIC input, MIC1 with muting function

? Individual volume control

? Output: 70V, 100V, 4~16?

? LED indicator

? Short circuit protection & alarm

Specification

Model	PB-3060	PB-3120	PB-3240	PB-3360	PB-3480
-------	---------	---------	---------	---------	---------

Rated output power	60W	120W	240W	360W	480W
Max output power	90W	180W	360W	540W	720W
Output	70V, 100V, 4~16?				
AUX output level	600?, 1V (0dBV)				
Input level	MIC 1,2,3: 600?, 6mV (unbalanced)				
	AUX 1,2: 10K?, 250mV (unbalanced)				
Frequency response	100Hz-16KHz (± 3 dB)				
T.H.D.	<0.1% at 1KHz, 1/3 rated output power				
S/N ratio	MIC 1,2,3: ?66dB				
	AUX 1,2: ?70dB				
Tone control effect	Bass: ± 10 dB at 100Hz				
	Treble: ± 10 dB at 10KHz				
Power consumption	90W	180W	360W	720W	960W
Protection	AC fuse, DC voltage, Overload, Short circuit				
Muting function	MIC1 overrides other input signals at 0~30dB				
Power supply	AC220~230V/50Hz				
Product dimension (mm)	430x260x88			430x388x88	
Net Weight (kg)	6.0	8.0	10.0	12.6	16.3

Product Gallery

