

PB-480MZ/PB-650MZ 4 Zone Digital Mixer Amplifier with MP3/Tuner/Bluetooth/Remote Paging

Product ID: PB-480MZ/PB-650MZ



Short Description

Rated output power: 480W; 650W

Combined with MP3/USB/FM tuner/Bluetooth/Remote paging

3 MIC input, 2 RCA line input, 1x6.3mm AUX input

Description

? Combined with MP3/USB/FM tuner/Bluetooth/Remote paging function

? 3 MIC input, MIC1 with muting function

? 2 RCA line input, 1 6.3mm AUX input

? 3 Input channel volume individual control & tone control

? Master, basee and treble volume control

? 4 Zone speaker 100V output

? RJ45 jack for zone selectable remote mic (EM-4)

? LED selector and indicators

? Short circuit protection & alarm

Specification

Model	PB-480MZ	PB-650MZ
Rated output power (RMS)	480W	650W
Input	MIC 1,2,3: -50dB / 20K? (balanced)	
Sensitivity/Impedance	Line 2,3: 0dB / 20K? (unbalanced)	
Output leve / Impedance	100V (21?)	100V (16?)
Frequency response	80Hz-18KHz (-3dB)	
T.H.D.	<0.1% at 1KHz, 1/3 rated output power	
S/N ratio	>81dB	
Tone control	100Hz, 10KHz, ±10dB	
Protection	AC fuse, DC voltage, Overload, Short circuit	
Muting function	MIC1 overrides other input signals at 0~30dB	
Power supply	AC220~230V/50~60Hz	
Product dimension (WxDxH)	420x320x88mm	
Net Weight (Kg)	5.5	5.7

Product Gallery

