

PB-3060Z/PB-3120Z/PB-3240Z/PB-3360Z/PB-3480Z 6 Zone Mixer Amplifier

Product ID: PB-3060Z/PB-3120Z/PB-3240Z/
PB-3360Z/PB-3480Z



Short Description

Rated output power: 60W/120W/240W/360W/480W
2 AUX input, 3 MIC input, 1 AUX output for link

Description

- ? 2 AUX input, 3 MIC input, MIC1 with muting function
- ? Individual input volume control
- ? Output: 70V, 100V, 8?
- ? LED indicator
- ? Short circuit protection & alarm

Specification

Model	PB-3060Z	PB-3120Z	PB-3240Z	PB-3360Z	PB-3480Z
Rated output power	60W	120W	240W	360W	480W
Max output	90W	180W	360W	540W	720W

power					
Output	70V, 100V, 8?				
AUX output level	600?, 1V (0dBV)				
Input level	MIC 1,2,3: 600?, 6mV (unbalanced)				
	AUX 1,2: 10K?, 250m (unbalanced)				
Frequency response	100Hz-16KHz (± 3 dB)				
T.H.D.	<0.1% at 1KHz, 1/3 rated output power				
S/N ratio	MIC 1,2,3: ?66dB				
	AUX 1,2: ?70dB				
Tone control effect	Bass: ± 10 dB at 100Hz				
	Treble: ± 10 dB at 10KHz				
Power consumption	120W	240W	480W	720W	960W
Protection	AC fuse, DC voltage, Overload, Short circuit				
Muting function	MIC1 overrides other input signals at 0~30dB				
Power supply	AC220~230V/50Hz				
Product dimension (WxDxH) mm	430x260x88				430x388x88
Net Weight (Kg)	6.0	8.0	10.0	12.6	16.3

Product Gallery

