

EA-8412 8x4 Matrix Mixer Amplifier with Paging

Product ID: EA-8412



Short Description

Rated output power: 120Wx4ch
4 MIC input, 4 line input, 4 Ch output
With remote paging MIC input

Description

- ? Rated output power: 120Wx4ch
- ? 4 XLR Balanced jack and 1/4" phone jack for CH1-4 input
- 4 1/4" phone jack and RCA jack for CH5-8 input
- ? 8 Gain control for each input
- ? 4 channel Euro Block for output
- ? Output Level control with 2 tone control and mute switch
- ? With remote paging MIC input (RJ45 interface)
- ? Talkover switch for Ch1
- ? Phantom Power switches for CH1 and CH2-4
- ? LED indicators: Power, SIG, CLIP for each input channel and SIG,-10dB,0dB, CLIP,PROT,for each output

Specification

Model		EA-8412
Channel Quantity		4 CH
Rated Output Power		120Wx4CH
Output / Impedance		100V(83?) 70V(42?)
Input sensitivity /Impedance	Mic Input	-50dB~ - 6dB / 20K? Balanced
	Line Input	-30dB~ + 14dB / 20K? Balanced
Frequency Response (± 1 dB)		20Hz - 20kHz
T.H.D		<0.1%
Closstalk		>70dB
Equalization	Input	High : 12 kHz $\pm$ 15 dB Mid : 2.5 kHz $\pm$ 15 dB Low : 80 Hz $\pm$ 15 dB
	Output	High : 12 kHz $\pm$ 15 dB Low : 80 Hz $\pm$ 15 dB
S/N Ratio		>90dB
Power Source		AC 230 V, 50/60Hz
Net Weight		6.3Kg
Dimensions (W x H x D)		420 x 88 x 320mm

Product Gallery

