

DA-8060/DA-8125/DA-8250 8 Channels Digital Power Amplifier

Product ID: DA-8060/DA-8125/DA-8250



Short Description

Output: 8*60W/8*125W/8*250W

9 CH (8 master + 1 standby) output

Each channel independent input/output

Independently volume control

Description

This series amplifier is an 8-master-1-standby-amplifier integrated with 8 power amplifier modules and 1 sub-module which can control 8 broadcast intervals. When one of the sections fails, the standby channel can also be used to continue broadcasting.

- ? Touch screen design, user-friendly
- ? 9 channels: 8 main amplifiers, 1 standby amplifier
- ? Active/standby switching function: 8 main amplifiers in 8 channels
- ? Independent input and output interfaces for each channel
- ? Independently volume adjustment
- ? Protection of over voltage, over current, high temperature and short circuit

Specification

Model	DA-8060	DA-8125	DA-8250
Channel	8		
Rated power per channel	60W	125W	250W
Rated output power	100V		
Input sensitivity	1VRMS		
S/N ratio	?80dB		
Frequency response	80Hz-15kHz (±3dB)		
T.H.D.	?0.5%		
Power requirement	AC180-260V/50-60Hz		
Net weight (Kg)	24	26	28
Product dimensio (mm)	484x470x176		

Product Gallery

