

H-F08/2 8 Channel Professional Mixing Console

Product ID: H-F08/2



Short Description

4 CH Mono & 4 CH Mic input
2 channel stereo input

Description

- ? 4 channels Mono and 4 channels MIC input, 2 channel stereo input
- ? High-performance microphone pre-amplifiers with switchable phantom power
- ? 3-band channel EQ and high-pass filters
- ? Build-in channel compressors
- ? Smooth 60-millimeter faders & Illuminated channel on switches
- ? Bright meters for visual level monitoring

Specification

Model	H-F08/2
-------	---------

Max output level	19dBm(1Hz, THD=0.5%)
Phones output	40mW(1Hz, THD=0.5%, 200?)
Input type	XLRx4, RCAx4
Frequency response	20Hz-20KHz
Residual noise SNR	-75dB
S/N	71dB
T.H.D.	?0.05% (1KHz, 0.775V)
EQ	LOW: 80Hz±15dB
	MID: 2.5KHz±15dB
	HIGH: 12KHz±15dB
Gain control	Mono: -55dB~0dB
	Sereo: -10dB~0dB
Power supply	AC220V 50~60Hz
Power consumption	25W
Dimension (LxWxH) (mm)	400x400x45
Net weight (Kg)	4.41