

PB-3000/PB-3500/PB-4000 Power Amplifier

Product ID: PB-3000/PB-3500/PB-4000



Short Description

Rated output power: 1000W/1500W/2000W
100V/70V and 4~16 Ω speaker output

Description

? Transform isolated 100V, 70V and 4 Ω speaker output

? 5 LED indicator status display

? XLR socket and 6.3mm jack for additional mixer/amplifier link

? Output short-circuit protection and display

Specification

Model:	PB-3000	PB-3500	PB-4000
Rated output power	1000W	1500W	2000W
Input sensitivity	1V		
S/N	>90dB		
Frequency response	80Hz-15KHz (± 3 dB)		
THD 4 Ω /1kHz	<0.5%		
Output mode	70V, 100V or 4-16 Ω		

Indicators	Power, clip, signal, prot, temp		
Protection	Power turn on/off, overheating, DC voltage, short circuit		
Power requirements	AC 220~240 V / 50 ~ 60 Hz		
Gross weight (Kg)	33.5	38.5	42.5
Net weight (Kg)	30	35	39
Dimensions (mm)	132x483x480		

Product Gallery

